

# CST2310

Concierge station for VX2300 system (2 wires)



**3.5" TFT LCD monitor with  
OSD and real time clock**

**Backlit capacitive touch  
buttons**

**Hands free or handset**

**PC programming via USB**

**Stainless steel desktop kit  
included**

The Kristallo series has an elegant, sophisticated design that gives prestige to the device, making it a part of the furnishing.

The casing is made of a polished, white glass-effect polycarbonate.

The high-resolution 3.5" TFT LCD monitor offers sharp images and a wide view, soft-touch buttons allow easy and intuitive function management.



## KRISTALLO Series 3.5" concierge station for VX2300 system (2 wires)

3.5" TFT OSD LCD monitor with Real Time Clock, power supply by BUS, capacitive touch backlit keyboard, 2 direct buttons for Day/ Night mode and open door, 2 two-tone status LEDs. Complete with support.

### Technical characteristics

<b>Display</b>	3.5" TFT 320x240 pixel with OSD and real time clock	
<b>Handset</b>	Hands free with handset	
<b>Hands free</b>		
<b>Buttons</b>	Alphanumeric keypad Operating mode <sup>1</sup> Door open <sup>1</sup>	(All buttons are backlit and capacitive touch)
<b>Main Features</b>	<ul style="list-style-type: none"> <li>• Connectable to any place along the BUS between power supply and last intercom</li> <li>• Additional handset or videophone working in parallel to connect into a 2<sup>nd</sup> guard room (to answer calls and open the door)</li> <li>• Intercommunication facility</li> <li>• Door panel Recall facility</li> <li>• Day, Night and OFF Mode facility</li> <li>• Additional relay services activation</li> <li>• Programming via USB and PC SW VX2X00</li> </ul>	
<b>Main Functions</b>	<ul style="list-style-type: none"> <li>• Receive calls from door panels</li> <li>• Receive calls from apartments</li> <li>• Make call towards door panels (Recall)</li> <li>• Make calls towards apartments</li> <li>• Forward calls from door panels to apartments (with holding state for the door panel during the call to the apartment)</li> <li>• Apartment missing calls memory list on screen (with Apt.no. and Time of the event)</li> <li>• Apartment alarm calls memory list on screen (with Apt.no. and Time of the event)</li> <li>• Make intercommunication calls between 2 apartments</li> <li>• Activate door locks</li> <li>• Activate additional relays</li> <li>• System status check LED (system busy due to a door call or intercommunication call)</li> <li>• Night Mode: All calls go directly to relevant apartments except for Concierge ID 1</li> <li>• Day Mode: All calls are intercepted by the Concierge unit</li> <li>• OFF Mode: Concierge not in use</li> <li>• In Night Mode the 2<sup>nd</sup> device (monitor or intercom) in parallel to the Concierge unit could get the call with the possibility to disable the call during the Day Mode by pressing Privacy button</li> </ul>	
<b>LED<sup>2</sup></b>	Operating mode/Busy (3 colors) Door status (2 colors) Speech	
<b>Adjustments</b>	Hands free audio level Ring audio level	Brightness Hue Contrast
<b>Programming</b>	Access code Date and time	Number of rings Melody type
<b>Inputs</b>	Local bell	
<b>Outputs</b>	Dry contacts	
<b>Video mode</b>	Modulated	
<b>Power supply</b>	Supplied by BUS or 12V additional PSU	
<b>Mounting</b>	Tabletop	
<b>Finishes</b>	White <b>CST2310/W</b>	
<b>Desktop kit</b>	Stainless steel desktop kit (included)	

<sup>1</sup> Function buttons are used for multiple functions.

<sup>2</sup> The operation of some LED's and the functions described may require additional cabling.

