

# KRV72

KRISTALLO Series 3.5" videophone  
with handset and hands-free for VX2200 system (6 wires)



KRV72/W



KRV72/B

The Kristallo series has an elegant, sophisticated design that gives prestige to the device, making it a part of the furnishing.

The casing is made of a polished, white or black glass-effect polycarbonate.

The high-resolution 3.5" TFT LCD monitor offers sharp images and a wide view, soft-touch buttons allow easy and intuitive function management.

## 3.5" TFT LCD monitor

## Backlight capacitive touch buttons

**4 function LED's**  
including door monitoring LED

## Up to 10 units in the same apartment

**Up to 4 programmable push buttons for intercommunication**  
with another apartment or another room of the same apartment

**Adjustments and programming**  
Call tone volume, speech volume, hue, brightness, melody and rings, privacy and service time, intercommunication and buttons backlight

## Surface or tabletop installation

## KRISTALLO Series 3.5" videophone with handset and hands-free for VX2200 system (6 wires)

TFT LCD monitor, 8 capacitive backlight touch buttons for controlling: Conversation/Camera recall/Push to talk, Door open/Concierge call, Service, Privacy/Reject call, up to 4 programmable push buttons for intercommunication (with another apartment or another room of the same apartment).

Timed privacy service.

4 function LEDs: Conversation/Camera recall, Door open/Concierge call, Service, Privacy on.

Adjustments: Call tone and Speech volume, Number of rings, Brightness, Hue.

Programming: Number of rings, Melody type, Intercommunication, Service duration, Privacy duration, Buttons backlight.

Local bell, Alarm inputs and Service button output. Coax/Balanced video mode.

Up to 10 units in the same apartment.

Wall mounted or table top, white or black finishes.



### Technical characteristics

<b>Display</b>	3.5" TFT 320x240 pixel	
<b>Handset / Hands free</b>	Hands free with handset	
<b>Buttons</b>	8 capacitive touch buttons	
<b>Buttons / Services <sup>1</sup></b>	Conversation/Camera recall/Push to talk Door open/Concierge call Service Privacy/Reject call Up to 4 programmable push buttons for intercommunication (with another apartment or another room of the same apartment)	
<b>Privacy</b>	Yes, timed	
<b>LED<sup>2</sup></b>	Conversation/Camera recall Door open/Concierge call	Service Privacy on
<b>Adjustments</b>	Speech volume Call tone volume	Brightness Hue
<b>Programming</b>	Number of rings Melody type Intercommunication	Service duration Privacy duration Buttons backlight
<b>Inputs</b>	Local bell, Alarm	
<b>Outputs</b>	Service button	
<b>Video mode</b>	Coax/Balanced	
<b>Max number of units</b>	Up to 10 units in the same apartment (using additional 12V PSU)	
<b>Mounting</b>	Surface or tabletop	
<b>Finishes</b>	White <b>KRV72/W</b> Black <b>KRV72/B</b>	
<b>Desktop kit</b>	<b>KRV931</b>	

<sup>1</sup> Some buttons are used for multiple functions.

<sup>2</sup> The operation of some LED's and the functions described may require additional cabling.

### Accessories



**KRV931  
Desktop kit**

